

Rotary actuator for ball valves

- Nominal torque 2 Nm
- Nominal voltage AC 230 V
- Control 3-point



Technical data Electrical data Nominal voltage AC 230 V Nominal voltage frequency 50 Hz AC 207...253 V Nominal voltage range 1 W Power consumption in operation Power consumption for wire sizing 1 VA Connection supply / control Cable 1 m, 3 x 0.75 mm² Parallel operation No **Functional data** Torque motor Min. 2 Nm Manual override Gear disengagement with hand crank 105 s / 90° Running time motor Sound power level motor max. 35 dB(A) Position indication Mechanical Safety Protection class IEC/EN II Protective insulated Degree of protection IEC/EN EMC CE according to 2004/108/EC Low voltage directive CE according to 2006/95/EC Certification IEC/EN IEC/EN 60730-1 and IEC/EN 60730-2-14 Mode of operation Type 1 Rated impulse voltage supply / control 4 kV Control pollution degree 3 -7...50°C Ambient temperature Non-operating temperature -40...80°C Ambient humidity 95% r.h., non-condensing

Safety notes



Weight

 This device has been designed for use in stationary heating, ventilation and air conditioning systems and is not allowed to be used outside the specified field of application, especially in aircraft or in any other airborne means of transport.

Maintenance-free

0.27 kg

• Caution: Power supply voltage!

Maintenance

Weight approx.

- Only authorised specialists may carry out installation. All applicable legal or institutional installation regulations must be complied during installation.
- The actuator is to be protected against moisture. It is not suitable for outdoor applications.
- The correct functioning of the strain relief for the cable in the actuator housing is to be checked.
- The installer must check for correct principle of operation after installation.
- The device may only be opened at the manufacturer's site. It does not contain any parts that can be replaced or repaired by the user.
- The device contains electrical and electronic components and is not allowed to be disposed of as household refuse. All locally valid regulations and requirements must be observed.



Product features

Direct mounting Simple direct mounting on the ball valve with only one screw. The mounting orientation

in relation to the ball valve can be selected in 90° steps.

Manual override Manual override possible with lever (the gearing is disengaged as long as the self-

resetting lever is pressed).

High functional reliability The actuator switches off automatically when the end stops are reached. Pulse

duration ≥ 0.5 s

Combination valve/actuator Refer to the valve documentation for suitable valves, their permitted medium

temperatures and closing pressures.

Electrical installation




Notes

· Caution: Power supply voltage!

Wiring diagrams

AC 230 V, 3-point



Y2 A - AB = 0%


Cable colours:

1 = blue

2 = brown

3 = white

AC 230 V, open-close



Y2	
7	A - AB = 0%

Cable colours:


1 = blue


2 = brown

3 = white

Dimensions [mm]

Dimensional drawings





Further documentation

- Overview Valve-actuator combinations
- Data sheets for ball valves
- · Installation instructions for actuators and/or ball valves
- · General notes for project planning